



IS540.1

SAFETY INSTRUCTIONS
ENGLISH/JAPANESE



i.safe MOBILE

IS540.1 | MODEL M540A01
Document No. 1058MM09REV00
Version: 2023-09-11

i.safe MOBILE GmbH
i_Park Tauberfranken 10
97922 Lauda-Koenigshofen
Germany

Tel. +49 9343 60148-0
info@isafe-mobile.com
www.isafe-mobile.com

(c) 2023 i.safe MOBILE GmbH

Template: TEMPMM01REV10

CONTENTS

English.....	4
Japanese.....	6

ENGLISH

EX MARKINGS

▶ ATEX:

- Ⓜ II 2G Ex ib IIC T4 Gb
- Ⓜ II 2D Ex ib IIIC T135°C Db
- EU Type Examination Certificate:
EPS 22 ATEX 1 341 X
- CE-designation: C € 2004

▶ IECEx:

- Ex ib IIC T4 Gb
- Ex ib IIIC T135°C Db
- IECEx Certificate: IECEx EPS 22.0076X

▶ Japan Ex:

- Ex ib IIC T4 Gb
- Ex ib IIIC T135°C Db
- TIIS Certificates: TC22900X, TC22901X

▶ Temperature range:

- 20°C ... +55°C (EN/IEC 60079-0)
- 10°C ... +55°C (EN/IEC 62368-1)

▶ Manufactured by:

- i.safe MOBILE GmbH**
i_Park Tauberfranken 10
97922 Lauda-Koenigshofen
Germany



EX-RELEVANT SAFETY REGULATIONS

Use of this device assumes that the operator observes the conventional safety regulations and has read and understood Operating Manual, Safety Instructions and certificate.

When used in explosion hazardous areas, the following Safety Instructions must also be complied with:

- ▶▶ Inside explosion hazardous areas the covers of all interfaces (USB, ISM Interface) must be closed.
- ▶▶ Within explosion hazardous areas, the following accessories may be used when connected to the ISM interface:
 - ▶ the Headset **IS-HS2A.1**
 - ▶ the Headset **IS-HDHS1x.1**
 - ▶ the PTT Button **IS-PTTB1A.1** together with the Headset **IS-HDHS1x.1**
 - ▶ the PTT Button **IS-PTTB1A.1** without Headset **IS-HDHS1x.1**
 - ▶ other accessories approved by **i.safe MOBILE GmbH**.The 16-pin ISM connector of the accessory must be securely fastened to the ISM interface.
- ▶▶ If the PTT Button **IS-PTTB1A.1** is connected to the ISM interface of the device together with the Headset **IS-HDHS1x.1**, the connection between the **IS-PTTB1A.1** and the Headset **IS-HDHS1x.1** can be disconnected and reconnected in explosion hazardous areas. When using the **IS-PTTB1A.1** without the Headset **IS-HDHS1x.1**, the unused cable end of the **IS-PTTB1A.1** may remain open in explosion hazardous areas.
- ▶▶ When using accessories with Velcro fasteners (e.g. Headset **IS-HDHS1B.1**), the Velcro fastener may only be adjusted outside explosion hazardous areas.

- » To ensure the IP-protection, it has to be ensured that all gaskets are present and functional. There must be no large gap between the two halves of housing and between the battery compartment cover and housing.
- » The device may only be charged outside explosion hazardous areas using the **i.safe PROTECTOR 2.0** USB-C Cable or other charging equipment approved by **i.safe MOBILE GmbH**.
- » The microSD cards type **IS-SD164.1** and **IS-SD1128.1** or microSD cards which comply with the intrinsic safety entity parameters mentioned in the certificate, may be used in the corresponding slot in the hazardous area.
- » Nano-SIM cards which comply with the intrinsic safety entity parameters mentioned in the certificate, may be used in the corresponding slot in the hazardous area.
- » The device may only be charged at ambient temperatures between 0°C ... +45°C.
- » The device may not be exposed to any aggressive acids or alkalis.
- » The device may only be used in zones 1, 2, 21, or 22.

FAULTS AND DAMAGES

If there is any reason to suspect that the safety of the device has been compromised, it must be withdrawn from use and removed from any ex-hazardous areas immediately. Measures must be taken to prevent any accidental restarting of the device. The safety of the device may be compromised, if, for example:

- » Malfunctions occur.
- » The housing of the device shows damage.
- » The device has been exposed to excessive loads.
- » The device has been stored improperly
- » Markings or labels on the device are illegible.

We recommend that a device displaying errors or in which an error is suspected be sent back to **i.safe MOBILE GmbH** to be checked.

INFORMATION CONCERNING SAR CERTIFICATION (SPECIFIC ABSORPTION RATE)

The SAR limit of Europe is 2,0 W/kg for the head and body, 4,0 W/kg for the limbs. The device has been tested against this SAR limit. The highest SAR value reported under this standard during product certification for use at the ear is 1,27 W/kg and when correctly worn on the body is 1,23 W/kg, limbs is 2,3 W/kg.

This device was tested for typical body worn operations with the back of the handset kept 5 mm from the body. The device complies with RF specifications when used at 5 mm from the body. Belt clips, holsters and similar accessories used should not contain metallic components in the assembly. The use of accessories that do not satisfy these requirements may not comply with RF exposure requirements, and should be avoided.

FCC/IC STATEMENT

The FCC/IC declaration can be found at
www.isafe-mobile.com/en/support/downloads

日本語

EXマーキング

- › ATEX:
 - Ⓢ II 2G Ex ib IIC T4 Gb
 - Ⓢ II 2D Ex ib IIIC T135°C Db
 - EUタイプ試験証明書:
EPS 22 ATEX 1 341 X
 - CE認定: c€ 2004
- › IECEx:
 - Ex ib IIC T4 Gb
 - Ex ib IIIC T135°C Db
 - IECEx認定: IECEx EPS 22.0076X
- › 日本Ex:
 - Ex ib IIC T4 Gb
 - Ex ib IIIC T135°C Db
 - TIIS 認定: TC22900X, TC22901X
- › 温度範囲:
 - 20°C ... +55°C (EN/IEC 60079-0)
 - 10°C ... +55°C (EN/IEC 62368-1)
- › 製造元:
 - i.safe MOBILE GmbH
 - i_Park Tauberfranken 10
 - 97922 Lauda-Koenigshofen
 - Germany



連する安全規則

このデバイスの使用は、作業者が従来の安全規則を順守し、マニュアル、安全に関する指示書および証明書を読み、理解していることを前提としています。

爆発危険エリアで使用する場合、次の安全規定も遵守する必要があります：

- › 本デバイスを爆発危険エリアで使用する場合、すべてのインターフェースカバー (USB, ISM インターフェース) を完全に閉じる必要があります。
- › 爆発の危険がある区域内では、以下のアクセサリが ISM インターフェースと接続した状態で使用できません。
 - › IS-HS2A.1 ヘッドセット
 - › IS-HDHS1x.1 ヘッドセット
 - › IS-HDHS1x.1 ヘッドセットと併用する IS-PTTB1A.1 PTT ボタン
 - › IS-HDHS1x.1 ヘッドセットと併用しない IS-PTTB1A.1 PTT ボタン
 - › i.safe MOBILE GmbH 承認済みのその他のアクセサリ。
- › アクセサリの 16 ピン ISM コネクタは ISM インターフェースにしっかりと接続されている必要があります。
- › IS-PTTB1A.1 PTT ボタンをデバイスの ISM インターフェースに IS-HDHS1x.1 ヘッドセットと併用して接続している場合、爆発の危険がある区域で、IS-PTTB1A.1 と IS-HDHS1x.1 ヘッドセット間の接続の解除、再接続が可能です。

- » IS-PTTB1A.1 を IS-HDHS1x.1 ヘッドセットを併用せずに使用する場合は、爆発の危険がある区域では、IS-PTTB1A.1 の使用していないケーブルの端はオープンにしておいてください。
- » ベルクロファスナのついたアクセサリ（IS-HDHS1B.1 ヘッドセットなど）を使用する場合、ベルクロファスナの調整は爆発の危険がある区域外でのみ行うことが可能です。
- » IP保護を保証するため、デバイスにすべてのシーリングが適切に備わっていることを確認してください。デバイスの左右中間部およびバッテリーカバーとデバイスの間大きな隙間がないようにします。
- » このデバイスは、i.safe PROTECTOR 2.0 USB-Cケーブルまたはi.safe MOBILE GmbHにより承認されたその他の充電機器を使用して、爆発危険区域外でのみ充電することができます。
- » microSDカードタイプIS-SD164.1およびIS-SD1128.1、または証明書に記載されている本質安全接続パラメータに準拠するmicroSDカードは、危険区域の対応するスロットで使用できます。
- » 証明書に記載の本質安全接続パラメータに準拠するnano-SIMカードは、危険区域の対応するスロットで使用できます。
- » このデバイスは、+0 °C〜+45 °Cの周囲温度でのみ充電することができます。
- » デバイスを浸食性のある酸やアルカリにさらさないでください。
- » デバイスは、ゾーン1、2、21、または22でのみ使用できます。

欠陥と損傷

デバイスの安全性が損なわれたと疑われる理由がある場合は、デバイスの使用を中止し、直ちに危険区域から取り外してください。デバイスが誤って再始動しないようにするための対策が必要です。たとえば、次のような場合、デバイスの安全性が損なわれる可能性があります。

- » 誤作動の発生時。
- » デバイスのハウジングに損傷が見られる場合。
- » デバイスが過剰な負荷にさらされている場合。
- » デバイスの保管方法が不適切な場合。
- » デバイスのマークやラベルが読みにくい場合。

エラーが表示されたり、エラーが疑われるデバイスについては、i.safe MOBILE GmbH に返送して、確認することをお勧めします。

比吸収率 (SAR) 認証情報

欧州でのSARの制限値は、頭と体が2.0W/kg、手足が4.0W/kgです。この装置は、このSAR制限値に対してテストされています。耳に使用するための製品認証の際にこの規格で規定された最高のSAR値は1.27 W/kgです。体に正しく装着すると1.23W/kg、手足に装着すると2.3W/kgとなります。

この装置は、受話器の背面を本体から5mm離れた状態で、典型的な体に装着した状態で動作をテストしました。本体から5mm使用時にRF仕様を満たしています。使用されているベルトクリップ、ホルスター、および同様の付属品には、アセンブリに金属部品が含まれてはなりません。これらの要件を満たしていないアクセサリの使用は、RF 曝露要件を満たしていない可能性があり、避けるべきです。

FCC/IC宣言

FCC/IC宣言は、 www.isafe-mobile.com/en/support/downloads に記載されています。

WWW.ISAFE-MOBILE.COM